

# THE CONFIGURATION CHART OF TRANSISTORS

Type No.	hFE	Configuration No.	Type No.	hFE	Configuration No.
2SA473	O	M-3	2SC1914	F,V	A-6
2SA564	Q	A-9	2SC1914A	F,V	A-7
2SA672	B	H-2	2SC1959	Y	A-4
2SA679	F	N-1	2SC2323	B,G	N-1
2SA684A	Q	A-2	2SC1904	V	F-1
2SA725	G	A-6	2SC1904A	V	F-2
2SA725P	G	A-8	2SD381A	L	M-1
2SA733	P1,Q,R	A-4	2SD313R	E	M-5
2SA744	O	N-1	2SD325R	E	M-5
2SA750	E	A-4	2SD468	B	C-1
2SA786	R	H-1	2SD525	O	M-3
2SA798	G	G-1	2SD526	O,Y	M-3
2SA823	Q	A-1	2SD356	C,D	K-1
2SA834	P	A-1	2SD588A/A/	Q,R	J-1
2SA872A	E,F	A-5	2SD234	O	M-3
2SA898	B,V	F-1	2SD666	C	C-1
2SA899	V	F-1	(FET)	(100:)	
2SA899A	V	F-2	2SK131S	L	Q-1
2SA904	F	A-6	2SK19	BL,GR	E-1
2SA904A	F	A-7	2SK30A	Y	B-1
2SA906	G,H	A-6	2SK49	H1,H2	B-7
2SA979	F	G-1	2SK55	D	H-3
2SA1003	B,G	N-1	2SK61	GR	B-4, B-5
2SB507R	E	M-2	2SK30AD	2	B-1
2SB526	C,D	K-1	2SK30A-DB	---	B-6
2SB536A	L	M-1	3SK45	B	P-1
2SB596	Y	M-3			
2SB618A/A/	Q,R	J-1			
2SC372	Y	D-1, D-2			
2SC460	B	H-2			
2SC461	B	H-2			
2SC535	A,B	H-2			
2SC763	C	A-6			
2SC789	O	M-3			
2SC790	Y	M-3			
2SC828	R,S	A-9			
2SC945	P,Q1,R	A-4			
2SC945A	Q	A-5			
2SC1000	GR	D-2			
2SC1209	E	A-6			
2SC1213	B,C	H-2			
2SC1312	G	A-6			
2SC1344	D,E	H-2			
2SC1384	S	A-3			
2SC1400	E	A-5			
2SC1402	O	N-1			
2SC1419	B,C	M-4			
2SC1626	O	M-3			
2SC1649	P	A-1			
2SC1675	M	A-4			
2SC1775	E	A-4			
2SC1775A	E,F	A-5			
2SC1903	B,V	F-1			

<p>A-1</p> <p>hFE</p> <p>Type No.</p> <p>Lot No.</p> <p>E C B</p>	<p>A-2</p> <p>Suffix</p> <p>Trade mark</p> <p>hFE</p> <p>Type No.</p> <p>Lot No.</p> <p>E C B</p>	<p>A-3</p> <p>Trade mark</p> <p>hFE</p> <p>Type No.</p> <p>Lot No.</p> <p>E C B</p>
<p>A-4</p> <p>Type No.</p> <p>Lot No.</p> <p>hFE</p> <p>E C B</p>	<p>A-5</p> <p>Lot No.</p> <p>Type No.</p> <p>hFE</p> <p>Suffix</p> <p>E C B</p>	<p>A-6</p> <p>Lot No.</p> <p>hFE</p> <p>Type No.</p> <p>B C E</p>
<p>A-7</p> <p>Suffix</p> <p>Lot No.</p> <p>hFE</p> <p>Type No.</p> <p>B C E</p>	<p>A-8</p> <p>Orange dot</p> <p>Lot No.</p> <p>hFE</p> <p>Type No.</p> <p>B C E</p>	<p>A-9</p> <p>Trade mark</p> <p>hFE</p> <p>Type No.</p> <p>Lot No.</p> <p>E C B</p>
<p>B-1</p> <p>Type No.</p> <p>Lot No.</p> <p>IDSS</p> <p>S G D</p>	<p>B-2</p> <p>Trade mark</p> <p>IDSS</p> <p>Lot No.</p> <p>Type No.</p> <p>S G D</p>	<p>B-3</p> <p>Type No.</p> <p>Lot No.</p> <p>IDSS</p> <p>S G D</p>

<p>B-4</p> <p>Trade mark</p> <p>Lot No.</p> <p>IDSS</p> <p>Type No.</p> <p>D S G</p>	<p>B-5</p> <p>Type No.</p> <p>Lot No.</p> <p>IDSS</p> <p>D S G</p>	<p>B-6</p> <p>Type No.</p> <p>Lot No.</p> <p>Suffix</p> <p>D S G</p>
<p>B-7</p> <p>Type No.</p> <p>Lot No.</p> <p>IDSS</p> <p>G S D</p>	<p>C-1</p> <p>Type No.</p> <p>hFE</p> <p>Lot No.</p> <p>E C B</p>	<p>D-1</p> <p>Trade mark</p> <p>hFE</p> <p>Lot No.</p> <p>Type No.</p> <p>E C B</p>
<p>D-2</p> <p>Type No.</p> <p>hFE</p> <p>Lot No.</p> <p>E C B</p>	<p>E-1</p> <p>Trade mark</p> <p>IDSS</p> <p>Lot No.</p> <p>Type No.</p> <p>D S G</p>	<p>E-2</p> <p>Type No.</p> <p>IDSS</p> <p>Lot No.</p> <p>D S G</p>
<p>F-1</p> <p>Trade mark</p> <p>Type No.</p> <p>hFE</p> <p>Lot No.</p> <p>E C B</p>	<p>F-2</p> <p>Trade mark</p> <p>Type No.</p> <p>Suffix</p> <p>hFE</p> <p>Lot No.</p> <p>E C B</p>	<p>G-1</p> <p>Type No.</p> <p>Lot No.</p> <p>hFE</p> <p>B, C, E, C, B</p>

